

M2/M3 topside selection

Problem: Customer has an M2\M3 Board Part # 59-138-1048, or a M2\M3 control system Horizon # (58-138-2020, 2025, 2026). Topside is not functioning properly funny display. Customer needs to switch his filter cycle jumper between either A and middle or B and Middle.

When installing new position for jumper you should power down system first then do the Filter jumper, and then reset the battery backup. To reset the battery back up you need to jump out J36 for 30 seconds while power is off. Then un-jumper J36. Restart and away you go.

Topside for M2\M3 PCB or Control and set position

Horizon #	Balboa #	Position
Deluxe M-Series 58-138-1180	54128	Filter position A to middle
Deluxe M-Series 58-138-1182	54108	Filter position A to middle
Serial Standard Digital 58-138-1104	51057	Filter position B to middle
Serial Standard Digital 58-138-1102	53189	Filter position B to middle

Remember that all Deluxe Topsides go to position A and Middle
All Standard Topsides go to B and Middle.