MASTER SPAS

P/N 51999-07
MODEL MAS25

Balboa Instruments Incorporated
BALBOA INSTRUMENTS INC.
TUSTIN, CA.

LISTED 74254

Certified to comply with the limits for a class B computing device pursuant to subpart J of part 15 of the FCC rules

60 HZ

MODEL: WH-MAS25-CCAJ

PAT. NO. 4618797

USE COPPER CONDUCTOR ONLY
#8 AWG MIN. WIRE= 90°C
EMPLOYER UNIQUEMENT DES CONDUCTEURS DE CUIVRE.
TORQUE RANGE FOR TB1: 16-18 IN. LBS

FOR SUPPLY CONNECTIONS, USE CONDUCTORS SIZED ON THE BASIS OF 60°C AMPACITY BUT RATED MINIMUM OF 90°C.

Balboa Instruments Incorporated
01/12/06

MAS25 SYSTEM WIRING DIAGRAM

P/N 51999-07

TRANSFORMER

P.E.

(J21) PANEL COVERSION.

2 PIN = 2 OR 3 BUTTON PANEL
1 PIN = MINI PANEL

"A disconnecting means must be installed within sight from the equipment and at least 5 feet (1.52 m) from the inside walls of the pool, spa, or hot tub."

CONTROL PANEL (OPTIONAL)

CONTROL PANEL

TB1

AC INPUTS

GRN 5
RED 4
BLK 3
WHT 2
WHT

RED

FUSE 30A 250V

BRANCH CIRCUIT PROTECTION ONLY

J5 J13J4 J25

J37 J27 F4 J26 J7 J8 J39 J3 J35 J30

PUMP 2

WHT
RED
GRN

RED P-HI
BLK P-LOW
WHT P-COM

2 SPEED PUMP (OPTIONAL) ONLY FOR 240V PUMP 1 CONVERSION

3A FUSE

BLK

J23 30A/20A J21 J9 J20

HTR 4 Kw MAX.

OZONE GENERATOR

WHT

SENSOR

PRESSURE SWITCH

HI-LIMIT/FREEZE SENSOR

TEMPERATURE

K1 COM NO BLK

SNUBBER

SPA LIGHT

3A FUSE

BLK

120V TO 240V CONVERSION INSTRUCTIONS:

1. CONVERSION MUST BE PERFORMED BY A QUALIFIED, LICENSED ELECTRICIAN. HARDWIRE ONLY.
2. DISCONNECT FROM POWER & REMOVE CORD.
3. MOVE RED WIRE (TB1-1) TO (TB1-4) AS INDICATED BY DASHED LINES.
4. MOVE THE HEATER MODE SELECTOR (J23) ON THE CONTROL BOARD FROM 20A TO 30A POSITION.

CONVERSION DIAGRAM 120V TO 240V

TO CONTROL BOARD

RED TO RLY CONTACT
BLK TO RLY FRAME
BLK TO 30A FUSE
WHT TO J8
TO J5

GRN
EARTH GND

5 4 3 2 1 TB1

GRN RED BLK WHT WHT

POWER INPUTS

DEVICE	VOLTAGE	RATING
PUMP1	120/240V	15/12A
PUMP2	240V	12A
OZONE	120V	1A
SPA LIGHT	12V	12W
HEATER	120/240V	1KW/4KW

TOTAL OUTPUT AMPERAGE DRAW NOT TO EXCEED MAX INPUT RATING OF SPA.

If this unit is to be permanently connected, connect only to a circuit that is protected by a Class A ground fault circuit interrupter (G.F.C.I.).

RX FOR YOUR SPA